

# BCT64 通信協定

Modbus Register Address

| Address | Word | Item ( description ) | Code | Unit | Sign   | Range ( 十進制 )                               |
|---------|------|----------------------|------|------|--------|---------------------------------------------|
| 0000H   | 2    | Watt Hour            | 03H  | WH   | Unsign | 0~99999999                                  |
| 0002H   | 1    | Watt                 | 03H  | W    | Unsign | 0~9999                                      |
| 0003H   | 1    | Voltage              | 03H  | V    | Unsign | 0~9999                                      |
| 0004H   | 1    | Current              | 03H  | A    | Unsign | 0~9999                                      |
| 0005H   | 1    | dep 1                | 03H  |      | Unsign | 1: 0.000<br>2: 00.00<br>3: 000.0<br>4: 0000 |
| 0006H   | 1    | dep 2                | 03H  |      | Unsign | 1: 0.000<br>2: 00.00<br>3: 000.0<br>4: 0000 |
| 0010H   | 1    | Energy Reset         | 06H  |      | -----  | 1234 Hex : Reset $\Sigma$ Watt hour         |